




L1 MINUS 使用說明

歡迎使用L1 Minus 頭盔無線耳機，使用本產品請先閱讀此說明書。

本產品安裝在頭盔內部，可與手機無線連接實現接掛電話、播放音樂等功能。

1.按鍵介紹



2.如何安裝



3.配對及功能

(1).和手機配對,可接掛電話與播放音樂

L1 Minus 開機狀態下,手機可搜索到"L1" 字樣無線信號,點擊連接。連接後有"connected" 提示音，燈由紅藍燈交替閃爍變為藍燈6秒閃一次，斷開連接時有"Disconnected" 提示音。

注意:優先級:電話 > 音樂,當播放音樂時來電話,音樂暫停,通話結束後音樂自動恢復。

4.功能操作

(1).開機

開機狀態下長按A鍵3秒,未連接設備時紅藍燈交替閃爍,開機後有"POWER ON" 提示音,(開機後未連接任何設備5分鐘後自動關機)。

(2).關機

開機狀態下長按A鍵3秒,紅色指示燈長亮1秒,繼而熄滅,關機後有"POWER OFF"提示音。

(3).接聽來電

耳機和手機已配對狀態下,當來電報號10秒後無任何指令時自動接聽來電。操作成功後有"嗒" 提示音,來電時藍色指示燈快速閃爍。

(4).拒絕接聽來電

聽到來電後按住A鍵2秒,鬆開前有"嗒"提示音。

(5).終止通話

通話時按下話 A 鍵,鬆開前有"嗒" 提示音。

(6).語音撥號

無通話時, 雙擊A鍵。

(7).音樂播放/暫停控制

按下A鍵, 音樂播放時有"嗒"提示音。

(8).上/下曲

按住B鍵2秒播放下一曲,長按B鍵就下一曲跳下一曲直至鬆開B鍵。

(9).增減音量

按一下B鍵加大音量,到最大時有提示音,再繼續按B鍵音量減小,直到最小,循環。

(10).清除已配對設備

先按住A鍵再按住B鍵2秒,在紅燈閃三下時鬆手,清除配對記錄成功(如單獨連接一個設備時出現音樂卡,可做清除操作,再重新配對此設備)。

5.電池電量指示功能

(1).電池電量充足時,開機藍燈每6s閃1次;
(2).電池電量不足時,每1分鐘會有"Battery

Low" 提示音,紅燈6s閃一次;

(3).電池正在充電時,紅燈長亮;

(4).電池充電完成後(約2小時),紅燈滅,藍燈亮。

注: 電池容量180mAh,待機50小時,連續工作6小時。

6.日常保養

(1).切勿將耳機放置在溫度極高或極低的地方,最佳存放環境為-10度到+60度,否則會影響耳機的使用壽命;

(2).切勿將耳機暴露在明火之中,避免爆炸危險;

(3).切勿將耳機接觸尖銳對象,會造成劃痕或損壞;

(4).切勿嘗試拆卸耳機;

(5).如長時間不使用耳機,請確保放置在乾

燥的地方,若放置超過一個月要按時給與充電,以保證電池及耳機的工作性能。

低功率電波輻射性電機管理辦法

• 經型式認證合格之低功率射頻電機,非經許可,公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

• 低功率射頻電機之使用不得影響飛航安全及干擾合法通信;經發現有干擾現象時,應立即停用,並改善至無干擾時方得繼續使用。

前項合法通信,指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

頻率:2.4G
頻道數: 79個
發射功率: 0DBM
調變方式: 4.1n/4-DQPSK 和 8DPSK


天線規格: {
1.類型: 陶瓷天線
2.型號: ANT3216120A5T
3.尺寸規格: 5.2x2.0mm
4.增益: 1.5DB




L1 MINUS INSTRUCTION

Welcome to use L1 Minus wireless headset. Please read the Instruction manual before using. This kind of headset was installed in the helmet. With wireless technology, it is design to help answering phone calls, controlling the playing music status and so on.

1.Button introduction



2.How to install



3.Paring

(1).After paired with your phone, L1 Minus helps to answer phone calls, control the playing music status

Activate your wireless to search for " L1 " on your phone and operate to pair with it. (L1 Minus should be turned on before this step)



After connected successfully, the flashing blue and red light would change to 6s interval flashing blue light only. And there will be a short tone when connected or disconnected. Priority: Phone calls > Music, When there is a coming phone call, the playing music would suspend. After phone dialogue, the music would resume to play automatically.

4.How to operate

(1). Turn on

Press and hold "A" button until hearing a short tone (about 3 seconds). The blue & red light would flash alternatively. (Without any operation for 5 minutes, it would shut down automatically.)

(2)Turn off

Press and hold "A" button until hearing a short tone (about 3 seconds). The red light would fade after 1s.

(3)Answer a coming phone call

Without any operation for 10s, L1 Minus would help to answer the coming phone calls automatically under the pairing status. Once answering the call, you will hear a short tone " Di " and the blue light would flash quickly.

(4)Reject a coming phone call

Press and hold "A" button until hearing a short tone (it is about 2 seconds).

(5)Terminate dialogue

Press "A" button for once and you will hear a short tone " di "

(6)make a phone call

Double press "A" button to make a call under the not occupied status

(7)Play/pause music

Press "A" button for once to play or pause music

(8)Last/next song

Press and hold "B" button for 2s to play last song. Press and hold "B" button until reaching your favourite song.

(9)Up/low the volume

Press "B" button to raise the volume. When raised to its max, there will be a short tone. After getting to its max, press

"B" button to lower the volume. When lower to its min, there will be a short tone. After getting to its min, press " B " button to raise the volume.

(10)Clear the pairing record

First press the A key then press B key for 2 seconds, until the red light flashes for 3 times, you have been successfully cleared the pairing record. (You could clear the pairing record when the music is not clear or not smooth to listen. Repair it with your phone to improve the voice quality)

5.Power indication

(1) The blue light would flash every 6s when the power is full

(2) The red light would flash every 6s when the power is low and there will be a short tone every minute to remind you the low power status

(3) The red light keeps on status when it is charging
(4) The blue light keeps on after fully charged (about 2h)
Attention: the battery capacity is 180mAh and the standby time is 50h, which can work continually for 6h.

6.Maintainance

(1) Don't keep L1 Minus in the too hot or too cold place, the suitable temperature should be between -10°C and +60°C

(2) Don't put L1 Minus into fire, there is explosion danger.

(3) Don't keep L1 Minus close sharp objects.

(4) Don't try to open L1 Minus
(5) Keep L1 Minus in a dry and cool place when not used. And for better use please charge it regularly.

Low power radio wave radiation motor management

•Duly certified low power RF motor, without permission, any Organization or users are not allowed to change the frequency and increase power or change the features and functionality of the original design.

•Low power RF generator should not affect flight safety and legitimate traffic; when interference is found, shall be immediately deactivated.

Proper adjustment should be made until interference was terminated. The above-mentioned legitimate traffic means the working radio communications was legal according to the telecommunications act. Low-power RF power machine shall bear legitimate traffic or industrial, scientific and waves radiation of electrical equipment for medical use of interference.

Frequency : 2.4G

Channel quantity : 79

Transmit power : 0DBM

Adjust way : 4.1n/4-DQPSK & 8DPSK

- 1.Type: Ceramic radome
- 2.Model: ANT3216120A5T
- 3.Size: 5.2x2.0mm
- 4.Gain: 1.5DB